

ULX-D (JB) Group Channel List 【Standardモード】

使用可能ch数	6ch	6ch	8ch	8ch	10ch	10ch
周波数(MHz)	Group B1	Group B2	Group B3	Group B4	Group B5	Group B6
806.125	B1-1			B4-1	B5-1	B6-1
806.250		B2-1				
806.375			B3-1			
806.500				B4-2	B5-2	B6-2
806.625						
806.750		B2-2	B3-2			
806.875	B1-2					B6-3
807.000				B4-3	B5-3	
807.125						
807.250	B1-3		B3-3			B6-4
807.375				B4-4	B5-4	
807.500						
807.625			B3-4			B6-5
807.750		B2-3			B5-5	
807.875						
808.000				B4-5		B6-6
808.125	B1-4				B5-6	
808.250		B2-4				
808.375			B3-5			
808.500					B5-7	B6-7
808.625						
808.750	B1-5		B3-6	B4-6		
808.875					B5-8	B6-8
809.000		B2-5				
809.125				B4-7		
809.250			B3-7		B5-9	B6-9
809.375						
809.500		B2-6				
809.625	B1-6		B3-8	B4-8	B5-10	B6-10
809.750						